

marantz®

PM6006

高級綜合擴大機(內建數位輸入模組)



45w X 2ch

TOROIDAL TRANSFORMER

DAC MODE

SYMMETRIC LAYOUT

CURRENT FEEDBACK

CUSTOMISED COMPONENTS

Shotky Diodes

MM Phono

PURE DIRECT

green standby eco friendly

PM6006 為屢獲殊榮之 PM6005 的升級後繼型號，用家可以將各種數位訊源器材，直接接續到這部出色的兩聲道綜合擴大機，並利用其優越的 DAC，在播放各種新媒體格式時，能夠讓用戶體驗到出色得令人難以置信的聽覺享受。當然，我們在前級控制及後級功率放大線路上，依然採用著高級獨立零件——而不是在訊號傳輸路徑中採用單一的集成電路晶片。採用精心挑選的獨立零件，除了品質較集成電路更有保證外，這些零件亦能有效地強化音色表現，令輸出聲音更為細緻、清晰及通透。同時，我們也保留了低阻抗屏蔽的環形變壓器及客製化主電容與獨特的馬蘭士 HDAM 模塊。其他 PM6005 的原有功能——包括唱盤在內的 5 組模擬輸入端子、兩對支援雙線分音接駁的鍍金喇叭接柱等，在 PM6006 中全部繼續保留，更新增光纖及同軸數碼輸入端子，進一步加強其連接性。此機的 DAC 的音質已在不少高階產品中廣獲肯定的 24bit/192kHz CS4398。其數位訊號處理部分更是被額外的金屬外殼完全屏蔽，確保訊號傳輸時不會受到模擬訊號影響。總括而言，全新的 PM6006，是你步向全新音樂時代的成熟出眾橋樑。

Highlights

Integrated Current Feedback Amplifier with 2x 45W / 8 ohm rms

Further sound tuned with carefully selected components

Digital inputs (2x opt. / 1x coax.)

High quality DAC CS4398 and Marantz HDAM SA2

Fully shielded DAC unit; copper screws; rigid feet

Gold Plated Inputs/Outputs incl. Phono (MM) input

Marantz proprietary HDAM-SA3 circuits

Toroidal Transformer and high quality customized components

High quality Speaker Terminals (A / B switchable)

Available in black

Your Benefits

Wide bandwidth sound and enough power for medium size rooms

Unique Marantz audio experience

For extended connectivity and High Resolution Audio support (192kHz/24bit PCM)

Best sound quality from digital input signal

Eliminating interferences for purity of sound

Best connection for external sources

Wider dynamic range with lower distortion for the output stage

Delivering more power while causing less interferences

Improved connection to speakers

Perfectly matching CD6006 CD Player and NA6005 Network Audio Player



PM6006

高級綜合擴大機(內建數位輸入模組)



FEATURES	PM6006
Channels	2
Current Feedback Topology	•
Phono EQ: Standard	•
Digital in: optical / coaxial	• / •
DAC chip	CS4398
HDAM version	SA3, SA2
Toroidal Power Transformer	•
High Grade Audio Components	•
Customized Components	•
Aluminium extrusion heat sink	•
Balance / Bass / Treble / Loudness	• / • / • / •
OTHER	
Linear Drive Power Supply	•
Shottky diodes	•
Copper plated screws	•
Source Direct	•
Standby Mode	•
INPUTS / OUTPUTS	
Audio Inputs	5
Digital in: optical / coaxial	2 / •
Phono Input: MM	•
Audio Outputs	1
Gold Plated Cinch	•
Speaker A / B	•
Speaker Terminals	Metal (Gold) Screw
Number of Terminals	4
D-Bus	•
Headphone Out	•
Headphone Volume Control	•
SPECIFICATIONS	
Power Output (8 / 4 Ohm RMS)	45 W / 60 W
Frequency Response	10 Hz - 70 kHz
Total Harmonic Distortion	0.08 %
Damping Factor	100
Input Sensitivity	MM 2.2 mV / 47 kOhm
Signal to Noise Ratio	MM 83 dB
Input Sensitivity	High level 200 mV / 20 kOhm
Signal to Noise Ratio	High level 102dB (2V input)

GENERAL	
Available color: Black	•
Metal Front Panel	•
Power Consumption	395 W
Standby Consumption	0.3 W
Auto Power off	•
Detachable Power Cable	•
Remote Control	RC003PMCD
System Remote Function	•
Maximum Dimensions (W x D x H)	17.3 x 14.6 x 4.1 inches
Weight	17.2 lbs
EAN	
NA PM6006/U1B	699927141158 Black

完美搭配 CD6006



高級CD唱盤